

Brennan Engineering

BEPOC

MODBUS MAP

RPC APPLICATION

DATE: 2/7/2019

POC PCB FIRMWARE VERSION: 2.41

Revision History

Revision	Date	Description
0.01	10/31/12	Created
2.2	08/15/16	<ol style="list-style-type: none"> 1. Added valve testing functionality (just load verses time graph) (HMI) 2. Added 99 day min max rod load, PIP, Prod hp, run time, prod history (HMI) 3. Added Analog shut down on casing & tubing (POC & HMI) 4. Fixed POC ver reset from factory restore
2.3	04/25/17	<ol style="list-style-type: none"> 1. Added AO1 min max scale and vfd min max scale. 2. Added AO1 output mode 0-20mA/4-20mA 3. Added AO1-AO6 mA ouput and Raw values to modbus table 4. Added HG Pumping Units
2.31	05/25/17	Clear USER RAM 2 on boot so that unpopulated cards would be all 0s
2.32	12/07/18	<ol style="list-style-type: none"> 1. Changed IPA Calc.vi to use the lower 25% of the pumpcard nose to calc pump fillage
2.4	12/26/18	<ol style="list-style-type: none"> 1. Added linear pumping unit 2. Filtered AI values added 40044 as filt TC in ms adj from 1-10,000ms else 2000ms
2.41	02/05/19	<ol style="list-style-type: none"> 1. Added Pump force correction for fiberglass rod

00000 Registers

Common Command Functions 00001 - 00002

Note: Use Function Code 01 to Read these bits. Code 05/15 to Write these bits

REGISTER	# Coils	NAME	DESCRIPTION
1	1	RESET_MAL	Reset Malfunctions
2	1	CLEAR	Clear Alarms Flag

Motor Control Command Functions 00100-00102

Note: Use Function Code 01 to Read these bits. Code 05/15 to Write these bits

REGISTER	# Coils	NAME	DESCRIPTION
100	1	Global Off	Global Off
101	1	Stop Motor Host	Host Stop Motor
102	1	Start Motor Host	Host Start Motor

Application Specific Command Functions 00103-00200

Load Card Buffers

Note: Use Function Code 01 to Read these bits. Code 05 to Write these bits

103	1	Load Stored	Load Stored Cards into 5 Card Buffers
104	1	Load Shutdown 1	Load Shutdown Cards Set 1 Into 5 Card Buffers
105	1	Load Shutdown 2	Load Shutdown Cards Set 2 Into 5 Card Buffers
106	1	Load Standard	Load Standard Card into Single Card Buffer
107	1	Load Start	Load Start Card into Single Card Buffer
108	1	Load Pump Up	Load Pump Up Card into Single Card Buffer
109	1	Load Last Stroke	Load Last Stroke into Single Card Buffer

Digital Outputs 00225 - 00002

Note: Use Function Code 01 to Read these bits. Code 05/15 to Write these bits

REGISTER	# Coils	NAME	DESCRIPTION
229	12	DO5 - DO16	Physical Digital Outputs 5-16

10000 Registers

Digital Input Status

00225 - 00002

Note: Use Function Code 02 to Read these bits.

REGISTER	# Coils	NAME	DESCRIPTION
10321	10	DI1 - DI10	Physical Digital Inputs 1-10 Status

30000 Registers

Analog Input Status **30033 - 30352** **# Registers 320**

Use Function Code 04 to Read this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION																																										
30033	10		2		<table border="1" style="width: 100%;"> <thead> <tr> <th>Reg</th> <th>#</th> <th>F</th> <th>L</th> <th>A</th> <th>Name</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>30033</td> <td>2</td> <td>X</td> <td></td> <td></td> <td>CUR_SCALED_AI2</td> <td>Current Scaled Reading Analog 2</td> </tr> <tr> <td>30035</td> <td>2</td> <td>X</td> <td></td> <td></td> <td>CUR_DAY_AVE_AI2</td> <td>Current Scaled Daily Average Analog 2</td> </tr> <tr> <td>30037</td> <td>2</td> <td>X</td> <td></td> <td></td> <td>Reserved</td> <td>Reserved</td> </tr> <tr> <td>30039</td> <td>2</td> <td></td> <td>X</td> <td></td> <td>CUR_RAW_AI2</td> <td>Current Raw Reading Analog 2</td> </tr> <tr> <td>30041</td> <td>2</td> <td>X</td> <td></td> <td></td> <td>Current 8 Minute Avg</td> <td>Current Scaled 8 Minute Average</td> </tr> </tbody> </table>		Reg	#	F	L	A	Name	Description	30033	2	X			CUR_SCALED_AI2	Current Scaled Reading Analog 2	30035	2	X			CUR_DAY_AVE_AI2	Current Scaled Daily Average Analog 2	30037	2	X			Reserved	Reserved	30039	2		X		CUR_RAW_AI2	Current Raw Reading Analog 2	30041	2	X			Current 8 Minute Avg	Current Scaled 8 Minute Average
					Reg	#	F	L	A	Name	Description																																					
					30033	2	X			CUR_SCALED_AI2	Current Scaled Reading Analog 2																																					
					30035	2	X			CUR_DAY_AVE_AI2	Current Scaled Daily Average Analog 2																																					
					30037	2	X			Reserved	Reserved																																					
					30039	2		X		CUR_RAW_AI2	Current Raw Reading Analog 2																																					
					30041	2	X			Current 8 Minute Avg	Current Scaled 8 Minute Average																																					
30043	10				AI3 Status																																											
30053	10				AI4 Status																																											
30063	10				AI5 Status																																											
30073	10				AI6 Status																																											
30083	10				AI7 Status																																											

Analog Output Status **30353 - 30452** **# Registers 100**

Use Function Code 04 to Read this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION																																										
30353	10				<table border="1" style="width: 100%;"> <thead> <tr> <th>Reg</th> <th>#</th> <th>F</th> <th>L</th> <th>A</th> <th>Name</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>30353</td> <td>1</td> <td></td> <td></td> <td></td> <td>CUR_AO1_mA_x100</td> <td>Current Output Analog 1 mA x 100</td> </tr> <tr> <td>30354</td> <td>2</td> <td></td> <td></td> <td></td> <td>Reserved AO1</td> <td></td> </tr> <tr> <td>30356</td> <td>2</td> <td></td> <td></td> <td></td> <td>Reserved AO1</td> <td></td> </tr> <tr> <td>30358</td> <td>1</td> <td></td> <td></td> <td></td> <td>Reserved AO1</td> <td></td> </tr> <tr> <td>30359</td> <td>1</td> <td></td> <td></td> <td></td> <td>CUR_RAW_AO1</td> <td>Cur Raw Output Analog 1 0-1000</td> </tr> </tbody> </table>		Reg	#	F	L	A	Name	Description	30353	1				CUR_AO1_mA_x100	Current Output Analog 1 mA x 100	30354	2				Reserved AO1		30356	2				Reserved AO1		30358	1				Reserved AO1		30359	1				CUR_RAW_AO1	Cur Raw Output Analog 1 0-1000
					Reg	#	F	L	A	Name	Description																																					
					30353	1				CUR_AO1_mA_x100	Current Output Analog 1 mA x 100																																					
					30354	2				Reserved AO1																																						
					30356	2				Reserved AO1																																						
					30358	1				Reserved AO1																																						
30359	1				CUR_RAW_AO1	Cur Raw Output Analog 1 0-1000																																										
30363	10				AO2 Status																																											
30373	10				AO3 Status																																											
30383	10				AO4 Status																																											
30393	10				AO5 Status																																											
30403	10				AO6 Status																																											

Pump & Polish Rod Status **31848 - 31907** **# Registers 60**

Use Function Code 04 to Read this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
31848	12			x	Pump Position (in) x 100	x100 S16
31860	12			x	Pump Load (lb)	U16
31872	12			x	Polished Rod Position (in) x 100	x100 U16
31884	12			x	Polished Rod Load (lb)	U16
31896	12			x	Scan Rate (ms)	U16

Linear Pump Status **32356** **# Registers 1**

Use Function Code 04 to Read this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
32356	1				Output Ratio	

POC Status Registers 32501 - 32527 # Registers 28

Use Function Code 04 to Read this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
32501	1				Well State	Controller's Current State 0 - Invalid State 1 - Loss of Configuration 2 - Initialization State 3 - Power On Delay State 4 - Start Alert State 5 - Starting State 6 - Minimum Pump Strokes State 7 - Pumping Normal State 8 - Pumping Host State 9 - Pumping Timed Mode State 10 - Pumping HOA State 11 - Unable To Run State 12 - Pumping Bad Load State 13 - Pumping Bad Position State 14 - Stopping State 15 - Stopped State 16 - Unable To Stop State 17 - Load Recalibration State 18 - Load Not Calibrated State 19 - Programming Fault State 20-26 Reserved 27 - Valve Check State 28 - Main Board Diagnostic State 29 - Bottom Of Stroke Calibration State 30 - Reserved 31 - Downtime Pumpoff Setpoint State 32 - Downtime Malfunction State 33 - Downtime Peak Load State 34 - Downtime Minimum Load State 35 - Downtime HOA Off State 36 - Downtime Host Mode State 37 - Downtime Timed Mode State 38 - Downtime Pumping Bad Position State 39 - Downtime Pumping Bad Load State 40 - Downtime Low RPM State 41 - Downtime Global Off State 42 - Downtime Lost Power State 43 - Downtime Valve Check State 44 - Downtime Logic Expression State 45 - Reserved 46 - Downtime Low Fluid Load State 47 - Downtime Peak Torque State 48 - Downtime Low Power State 49 - Downtime NO RPM State 50 - Downtime No Crank State 51 - Downtime Peak Energy Management State

					52 - Downtime Operator Stop
					53 - Downtime IPA Cutoff
					54-69 Reserved
					70 - Malfunction Peak Load State
					71 - Malfunction Min Load State
					72 - Malfunction Malfunction Setpoint State
					73 - Malfunction Low RPM State
					74 - Malfunction Logic Expression State
					75 - Malfunction No RPM State
					76 - Malfunction No Crank State
					77 - Malfunction Peak Torque State
					78 - Reserved
					79 - Malfunction Low Fluid Load State
					80 - High Pressure Fault
					81 - High Vibration Fault
					82 - Brake Switch is Off
					83 - AI2 Fault
					84 - AI3 Fault
					85 - AI4 Fault
					86 - AI5 Fault
					87 - AI6 Fault
					88 - AI7 Fault
					89 - DI4 Fault
					90 - DI5 Fault
					91 - DI6 Fault
					92 - DI7 Fault
					93 - DI8 Fault
					94 - DI9 Fault
					95 - DI10 Fault
32502	1				Elapsed Time Hour
32503	1				Elapsed Time (Hours) in current state
32503	1				Elapsed Time Min and Sec
32503	1				High Byte: Elapsed Time(Minutes) in Low Byte: Elapsed Time(Seconds) in
32506	1				Stroke Period
32506	1				Number of seconds per stroke x100
32508	1				Current Load
32508	1				Current Scaled Load
32509	1				Current Position
32509	1				Current Scaled Position x100
32510	1				Current RPM
32510	1				Current Motor RPM
32511	2	X			Current Torque
32511	2	X			Current Torque
32513	2	X			Current HP
32513	2	X			Current HP
32515	1				Minimum Stroke Counter
32515	1				Number of Strokes in the Minimum Pump
32516	2		X		Rodometer
32516	2		X		Number of Strokes since Commission
32518	2		X		Pumpometer
32518	2		X		Number of Strokes since Last Pump
32525	1				Strokes per Minute
32525	1				SPMx100

Consecutive Violations 32528 - 32546 # Registers 19

Use Function Code 04 to Read this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
32530	1				Consecutive Peak Load	Number of Consecutive Peak Load Violations
32531	1				Consecutive Min Load	Number of Consecutive Min Load Violations

Historical Peak And Min Data **32567 - 32602** **# Registers 36**

Use Function Code 04 to Read this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
32569	1				Last Stroke Peak Load	Scaled Last Stroke Peak Load.
32572	1				Last Stroke Min Load	Scaled Last Stroke Min Load.

Inferred Production **32603-32607** **# Registers 5**

Use Function Code 04 to Read this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
32603	2	X			Total Inferred Production	Scaled Inferred Production x100 since
32605	1				Yesterday Inferred Production	Scaled Inferred Production x10 for Yesterday. Updated at Gage Off Time.
32606	1				Current Inferred Production	Scaled Inferred Production x10 since Gage Off
32607	1				Reserved	Reserved

Percent Run Time **32608 - 32611** **# Registers 4**

Use Function Code 04 to Read this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
32608	1				Yesterday Cycle Counter	Number of Pump Cycles Yesterday
32609	1				Current Cycle Counter	Number of Pump Cycles since Gauge Off (start stop cycles)
32610	1				Yesterday Percent Run	Yesterday Percent Runtime Updated at Gauge Off
32611	1				Current Percent Run	Percent Runtime Since Gage Off

Pump Card Status Registers **32612 - 32668** **# Registers 30**

Use Function Code 04 to Read this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
32612	1				NREVS	# Of Motor Revolutions Per Stroke
32613	1				Fluid Load	
32614	1				Pump Fillage	x 100
32615	1				Pump Card Peak Load	
32616	1				Pump Card Min Load	
32617	1				Net Stroke	
32618	1				Gross Stroke	
32619	2	X			Polished Rod HP Ave/Stroke	
32621	2	X			Pump HP Ave/Stroke	
32638	1				Todays Total Strokes	Since Gauge Off
32639	1				Yesterdays Total Strokes	
32640	1				Bouyed Rod Weight	lbs
32659	1				Current Pump Position	inches x 100
32660	1				Current Pump Load	lbf
32661	1				Damping Coefficient calculated	c X 1000
32662	1				Current Stroke Motor Revolutions	X 100
32663	1				Current SPM	X 100
32664	1				POC Continous Run Time Minutes	
32665	1				Calculated Surface Stroke Length	inches x 100
32666	1				Force Correction Factor	lbf x 10000 U16

Dynograph Cards **32669 - 36624** **# Registers 3696**

Use Function Code 04 to Read this Data

*NOTE: The following sections must be loaded before they are read. This can be accomplished with the command functions in the 0XXXX range. (Registers 103 - 109)

If POC is configured for downhole control, then the cards in the pump card buffer will correspond with the cards in the surface card buffer.

Register	# Regs	F	L	A	NAME	DESCRIPTION																																																																																											
32669	2035			X	Surface 5 Card Buffer	5 Card Buffer Stored Cards - Top Card is Most Recent																																																																																											
<table border="1"> <thead> <tr> <th colspan="7">Each Card is Organized As:</th> </tr> <tr> <th></th> <th>#</th> <th>F</th> <th>L</th> <th>A</th> <th>Name</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>Header</td> <td>2</td> <td></td> <td>X</td> <td></td> <td>TimeStamp</td> <td>Seconds Since Jan 1, 1970</td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Num Points</td> <td>Low Byte - Number of Points</td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Scaled Max Load</td> <td>Scaled Max Load Of Card</td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Scaled Min Load</td> <td>Scaled Min Load Of Card</td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Stroke Length</td> <td>Stroke Length x 100</td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Stroke Period</td> <td>Stroke Period x 100</td> </tr> <tr> <td>Card</td> <td></td> <td></td> <td></td> <td>X</td> <td>200 Point Pairs</td> <td></td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Position x 100</td> <td>Scaled Position x 100</td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Scaled Load</td> <td>Scaled Load</td> </tr> </tbody> </table>							Each Card is Organized As:								#	F	L	A	Name	Description	Header	2		X		TimeStamp	Seconds Since Jan 1, 1970		1				Num Points	Low Byte - Number of Points		1				Scaled Max Load	Scaled Max Load Of Card		1				Scaled Min Load	Scaled Min Load Of Card		1				Stroke Length	Stroke Length x 100		1				Stroke Period	Stroke Period x 100	Card				X	200 Point Pairs			1				Position x 100	Scaled Position x 100		1				Scaled Load	Scaled Load														
Each Card is Organized As:																																																																																																	
	#	F	L	A	Name	Description																																																																																											
Header	2		X		TimeStamp	Seconds Since Jan 1, 1970																																																																																											
	1				Num Points	Low Byte - Number of Points																																																																																											
	1				Scaled Max Load	Scaled Max Load Of Card																																																																																											
	1				Scaled Min Load	Scaled Min Load Of Card																																																																																											
	1				Stroke Length	Stroke Length x 100																																																																																											
	1				Stroke Period	Stroke Period x 100																																																																																											
Card				X	200 Point Pairs																																																																																												
	1				Position x 100	Scaled Position x 100																																																																																											
	1				Scaled Load	Scaled Load																																																																																											
34704	1045			X	Pump 5 Card Buffer	5 Card Buffer Stored Cards - Top Card is Most Recent																																																																																											
<table border="1"> <thead> <tr> <th colspan="7">Each Card is Organized As:</th> </tr> <tr> <th></th> <th>#</th> <th>F</th> <th>L</th> <th>A</th> <th>Name</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>Header</td> <td>2</td> <td></td> <td>X</td> <td></td> <td>TimeStamp</td> <td>Seconds Since Jan 1, 1970</td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Scaled Max Load</td> <td>Scaled Max Load Of Card</td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Scaled Min Load</td> <td>Scaled Min Load Of Card</td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Num Points</td> <td>Low Byte - Number of Points</td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Gross Stroke</td> <td></td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Net Stroke</td> <td>Net Stroke Length x100</td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Pump Fillage</td> <td>x 100</td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Fluid Load</td> <td></td> </tr> <tr> <td>Card</td> <td></td> <td></td> <td></td> <td>X</td> <td>100 Point Pairs</td> <td></td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Position x 100</td> <td>Scaled Position x 100</td> </tr> <tr> <td></td> <td>1</td> <td></td> <td></td> <td></td> <td>Scaled Load</td> <td>Scaled Load</td> </tr> </tbody> </table>							Each Card is Organized As:								#	F	L	A	Name	Description	Header	2		X		TimeStamp	Seconds Since Jan 1, 1970		1				Scaled Max Load	Scaled Max Load Of Card		1				Scaled Min Load	Scaled Min Load Of Card		1				Num Points	Low Byte - Number of Points		1				Gross Stroke			1				Net Stroke	Net Stroke Length x100		1				Pump Fillage	x 100		1				Fluid Load		Card				X	100 Point Pairs			1				Position x 100	Scaled Position x 100		1				Scaled Load	Scaled Load
Each Card is Organized As:																																																																																																	
	#	F	L	A	Name	Description																																																																																											
Header	2		X		TimeStamp	Seconds Since Jan 1, 1970																																																																																											
	1				Scaled Max Load	Scaled Max Load Of Card																																																																																											
	1				Scaled Min Load	Scaled Min Load Of Card																																																																																											
	1				Num Points	Low Byte - Number of Points																																																																																											
	1				Gross Stroke																																																																																												
	1				Net Stroke	Net Stroke Length x100																																																																																											
	1				Pump Fillage	x 100																																																																																											
	1				Fluid Load																																																																																												
Card				X	100 Point Pairs																																																																																												
	1				Position x 100	Scaled Position x 100																																																																																											
	1				Scaled Load	Scaled Load																																																																																											

35749	407				Single Surface Card Buffer	
					Each Card is Organized As:	
	#	F	L	A	Name	Description
Header	2		X		TimeStamp	Seconds Since Jan 1, 1970
	1				Num Points	Num Points
	1				Scaled Max Load	Scaled Max Load Of Card
	1				Scaled Min Load	Scaled Min Load Of Card
	1				Stroke Length	Stroke Length x 100
	1				Stroke Period	Stroke Period x 100
Card				X	200 Point Pairs	
	1				Position x 100	Scaled Position x 100
	1				Scaled Load	Scaled Load
36156	209				Single Pump Card Buffer	
					Each Card is Organized As:	
	#	F	L	A	Name	Description
Header	2		X		TimeStamp	Seconds Since Jan 1, 1970
	1				Scaled Max Load	Scaled Max Load Of Card
	1				Scaled Min Load	Scaled Min Load Of Card
	1				Num Points	Num Points
	1				Gross Stroke	
	1				Net Stroke	Net Stroke Length x 100
	1				Pump Fillage	x 100
	1				Fluid Load	
Card				X	100 Point Pairs	
	1				Position x 100	Scaled Position x 100
	1				Scaled Load	Scaled Load

Pump Card Status Registers **39703 - 39753** **# Registers 50**

Use Function Code 04 to Read this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
39703	1				Pump Intake Pressure (psi)	x 100
39748	1				Yesterday Oil Production (bbls)	x 10
39749	1				Yesterday Water Production (bbls)	x 10
39752	1				Current Oil Production (bbls)	x 10
39753	1				Current Water Production (bbls)	x 10

40000 Registers

Analog Inputs Config 40002 - 40043 # Registers 42

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION																																			
40002	6				AI1 Config	Analog Input 1 Configuration Registers																																			
<table border="1" style="width: 100%; border-collapse: collapse; background-color: yellow;"> <thead> <tr> <th>Register</th> <th>#</th> <th>F</th> <th>L</th> <th>A</th> <th>Name</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>40002</td> <td>2</td> <td>X</td> <td></td> <td></td> <td>FMAX</td> <td>Analog Input Channel 1 engineering value @ full scale</td> </tr> <tr> <td>40004</td> <td>2</td> <td>X</td> <td></td> <td></td> <td>FMIN</td> <td>Analog Input Channel 1 engineering value @ min scale</td> </tr> <tr> <td>40006</td> <td>1</td> <td></td> <td></td> <td></td> <td>RANGE</td> <td>Range 0 - 0 to 5 V 1 - 1 to 5 V 2 - 0 to 20 mA 3 - 4 to 20 mA</td> </tr> <tr> <td>40007</td> <td>1</td> <td></td> <td></td> <td></td> <td>UNITS</td> <td>Analog Input Channel Units 0 - psi 1 - deg F 2 - gpm 3 - bpd</td> </tr> </tbody> </table>							Register	#	F	L	A	Name	Description	40002	2	X			FMAX	Analog Input Channel 1 engineering value @ full scale	40004	2	X			FMIN	Analog Input Channel 1 engineering value @ min scale	40006	1				RANGE	Range 0 - 0 to 5 V 1 - 1 to 5 V 2 - 0 to 20 mA 3 - 4 to 20 mA	40007	1				UNITS	Analog Input Channel Units 0 - psi 1 - deg F 2 - gpm 3 - bpd
Register	#	F	L	A	Name	Description																																			
40002	2	X			FMAX	Analog Input Channel 1 engineering value @ full scale																																			
40004	2	X			FMIN	Analog Input Channel 1 engineering value @ min scale																																			
40006	1				RANGE	Range 0 - 0 to 5 V 1 - 1 to 5 V 2 - 0 to 20 mA 3 - 4 to 20 mA																																			
40007	1				UNITS	Analog Input Channel Units 0 - psi 1 - deg F 2 - gpm 3 - bpd																																			
40008	6				AI2 Config																																				
40014	6				AI3 Config																																				
40020	6				AI4 Config																																				
40026	6				AI5 Config																																				
40032	6				AI6 Config																																				
40038	6				AI7 Config																																				

Analog Output Control (Modbus Control) 40642 - 40650 # Registers 12

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
40642	1				AO2 Output (set mA via Modbus)	0=0mA 1000=20mA U16
40644	1				AO3 Output (set mA via Modbus)	0=0mA 1000=20mA U16
40646	1				AO4 Output (set mA via Modbus)	0=0mA 1000=20mA U16
40648	1				AO5 Output (set mA via Modbus)	0=0mA 1000=20mA U16
40650	1				AO6 Output (set mA via Modbus)	0=0mA 1000=20mA U16

Load Transducer Config **42151 - 42158** **# Registers 26**

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42151	1				Load Transducer Type	Load Transducer Type 0 - Non Calibrated 1 - Calibrated 50 K 2 - Calibrated 30 K 3 - Horse Shoe 4 - Other
42153	1				Load Maximum Weight	Calibrated Load Transducer Max Weight Scaled
42154	1				Load Transducer Gain	Load Transducer Gain
42155	1				Load Transducer Polarity	0 - Bipolar 1 - Unipolar
42156	1				RESERVED	Reserved
42157	1				RESERVED	Reserved
42158	1				Load Transducer Offset (A/D counts)	512 is default

Position Transducer Config **42177 - 42178** **# Registers 2**

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42177	1				Stroke Length (Calculated & overwritten by POC)	Stroke Length x100

Inferred Production **42188 - 42193** **# Registers 6**

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42188	1				Pump Diameter	Pump Diameter x100
42189	1				IPA K Factor	X 100
42193	1				IPA Water Cut	X 100

Control Registers **42195 - 42216** **# Registers 22**

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION																					
42195	1				Control Mode	Control Mode 0 - Surface 1 - Downhole 2 - Motor 3 - VFD - Surface 4 - VFD - Downhole																					
42196	1				Operation Mode	Operation Mode 0 - Normal Mode 1 - Timed Mode 2 - Host Mode																					
42197	1				Host Switch	Host Switch 0 - Host Off 1 - Host On																					
42198	2				Time Mode On	Time Mode On Hours: Minutes																					
<table border="1"> <thead> <tr> <th>Reg</th> <th>#</th> <th>F</th> <th>L</th> <th>A</th> <th>Name</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>42198</td> <td>1</td> <td></td> <td></td> <td></td> <td>Hour</td> <td>Time On Hours</td> </tr> <tr> <td>42199</td> <td>1</td> <td></td> <td></td> <td></td> <td>Minute</td> <td>Time On Minutes</td> </tr> </tbody> </table>							Reg	#	F	L	A	Name	Description	42198	1				Hour	Time On Hours	42199	1				Minute	Time On Minutes
Reg	#	F	L	A	Name	Description																					
42198	1				Hour	Time On Hours																					
42199	1				Minute	Time On Minutes																					
42200	2				Time Mode Off	Time Mode Off Hours: Minutes																					
<table border="1"> <thead> <tr> <th>Reg</th> <th>#</th> <th>F</th> <th>L</th> <th>A</th> <th>Name</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>42200</td> <td>1</td> <td></td> <td></td> <td></td> <td>Hour</td> <td>Time Off Hours</td> </tr> <tr> <td>42201</td> <td>1</td> <td></td> <td></td> <td></td> <td>Minute</td> <td>Time Off Minutes</td> </tr> </tbody> </table>							Reg	#	F	L	A	Name	Description	42200	1				Hour	Time Off Hours	42201	1				Minute	Time Off Minutes
Reg	#	F	L	A	Name	Description																					
42200	1				Hour	Time Off Hours																					
42201	1				Minute	Time Off Minutes																					
42202	1				Power On Delay	Power On Delay in Seconds																					
42203	1				Start Alert	Start Alert in Seconds																					
42204	1				Minimum Pump Strokes	Number of Strokes in Minimum Pump State																					
42205	1				Downtime Mode	Downtime Mode 0 - Manual Downtime 1 - Auto Downtime																					
42206	2				Downtime Period																						
<table border="1"> <thead> <tr> <th>Reg</th> <th>#</th> <th>F</th> <th>L</th> <th>A</th> <th>Name</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>42206</td> <td>1</td> <td></td> <td></td> <td></td> <td>Hour</td> <td>Downtime Period Hours</td> </tr> <tr> <td>42207</td> <td>1</td> <td></td> <td></td> <td></td> <td>Minute</td> <td>Downtime Period Minutes</td> </tr> </tbody> </table>							Reg	#	F	L	A	Name	Description	42206	1				Hour	Downtime Period Hours	42207	1				Minute	Downtime Period Minutes
Reg	#	F	L	A	Name	Description																					
42206	1				Hour	Downtime Period Hours																					
42207	1				Minute	Downtime Period Minutes																					
42215	1				HMI Start																						
42216	1				HMI Reset																						

Violation Configuration	42217 - 42243	# Registers 44
--------------------------------	----------------------	-----------------------

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION																																
42217	2				Violation Enable/Disable Config - Host Mode	Host Mode																																
<table border="1" style="margin: auto; background-color: yellow;"> <tr> <td style="padding: 2px;">0-Disable</td> <td style="padding: 2px;">1 - Enable</td> </tr> </table>							0-Disable	1 - Enable																														
0-Disable	1 - Enable																																					
<table border="1" style="margin: auto; background-color: yellow;"> <thead> <tr> <th style="padding: 2px;">Bit</th> <th style="padding: 2px;">Function</th> </tr> </thead> <tbody> <tr><td style="padding: 2px;">0 - 15</td><td style="padding: 2px;">Reserved</td></tr> <tr><td style="padding: 2px;">16</td><td style="padding: 2px;">Peak Load</td></tr> <tr><td style="padding: 2px;">17</td><td style="padding: 2px;">Min Load</td></tr> <tr><td style="padding: 2px;">18 - 20</td><td style="padding: 2px;">Reserved</td></tr> <tr><td style="padding: 2px;">21</td><td style="padding: 2px;">No RPM</td></tr> <tr><td style="padding: 2px;">22</td><td style="padding: 2px;">No Crank</td></tr> <tr><td style="padding: 2px;">23</td><td style="padding: 2px;">Belt Slippage</td></tr> <tr><td style="padding: 2px;">24 - 31</td><td style="padding: 2px;">Reserved</td></tr> </tbody> </table>							Bit	Function	0 - 15	Reserved	16	Peak Load	17	Min Load	18 - 20	Reserved	21	No RPM	22	No Crank	23	Belt Slippage	24 - 31	Reserved														
Bit	Function																																					
0 - 15	Reserved																																					
16	Peak Load																																					
17	Min Load																																					
18 - 20	Reserved																																					
21	No RPM																																					
22	No Crank																																					
23	Belt Slippage																																					
24 - 31	Reserved																																					
42219	2				Timed Mode	Timed Mode																																
<table border="1" style="margin: auto; background-color: yellow;"> <tr> <td style="padding: 2px;">0-Disable</td> <td style="padding: 2px;">1 - Enable</td> </tr> </table>							0-Disable	1 - Enable																														
0-Disable	1 - Enable																																					
<table border="1" style="margin: auto; background-color: yellow;"> <thead> <tr> <th style="padding: 2px;">Bit</th> <th style="padding: 2px;">Function</th> </tr> </thead> <tbody> <tr><td style="padding: 2px;">0 - 15</td><td style="padding: 2px;">Reserved</td></tr> <tr><td style="padding: 2px;">16</td><td style="padding: 2px;">Peak Load</td></tr> <tr><td style="padding: 2px;">17</td><td style="padding: 2px;">Min Load</td></tr> <tr><td style="padding: 2px;">18</td><td style="padding: 2px;">Logic Expression</td></tr> <tr><td style="padding: 2px;">19</td><td style="padding: 2px;">Peak Torque</td></tr> <tr><td style="padding: 2px;">20</td><td style="padding: 2px;">Low Motor RPM</td></tr> <tr><td style="padding: 2px;">21</td><td style="padding: 2px;">No RPM</td></tr> <tr><td style="padding: 2px;">22</td><td style="padding: 2px;">No Crank</td></tr> <tr><td style="padding: 2px;">23</td><td style="padding: 2px;">Belt Slippage</td></tr> <tr><td style="padding: 2px;">24 - 31</td><td style="padding: 2px;">Reserved</td></tr> </tbody> </table>							Bit	Function	0 - 15	Reserved	16	Peak Load	17	Min Load	18	Logic Expression	19	Peak Torque	20	Low Motor RPM	21	No RPM	22	No Crank	23	Belt Slippage	24 - 31	Reserved										
Bit	Function																																					
0 - 15	Reserved																																					
16	Peak Load																																					
17	Min Load																																					
18	Logic Expression																																					
19	Peak Torque																																					
20	Low Motor RPM																																					
21	No RPM																																					
22	No Crank																																					
23	Belt Slippage																																					
24 - 31	Reserved																																					
42221	2				Normal Mode	Same structure as 42217																																
<table border="1" style="margin: auto; background-color: yellow;"> <tr> <td style="padding: 2px;">0-Disable</td> <td style="padding: 2px;">1 - Enable</td> </tr> </table>							0-Disable	1 - Enable																														
0-Disable	1 - Enable																																					
<table border="1" style="margin: auto; background-color: yellow;"> <thead> <tr> <th style="padding: 2px;">Bit</th> <th style="padding: 2px;">Function</th> </tr> </thead> <tbody> <tr><td style="padding: 2px;">0 - 15</td><td style="padding: 2px;">Reserved</td></tr> <tr><td style="padding: 2px;">16</td><td style="padding: 2px;">Peak Load</td></tr> <tr><td style="padding: 2px;">17</td><td style="padding: 2px;">Min Load</td></tr> <tr><td style="padding: 2px;">18</td><td style="padding: 2px;">Logic Expression</td></tr> <tr><td style="padding: 2px;">19</td><td style="padding: 2px;">Peak Torque</td></tr> <tr><td style="padding: 2px;">20</td><td style="padding: 2px;">Low Motor RPM</td></tr> <tr><td style="padding: 2px;">21</td><td style="padding: 2px;">No RPM</td></tr> <tr><td style="padding: 2px;">22</td><td style="padding: 2px;">No Crank</td></tr> <tr><td style="padding: 2px;">23</td><td style="padding: 2px;">Belt Slippage</td></tr> <tr><td style="padding: 2px;">24</td><td style="padding: 2px;">Malfunction Setpoint</td></tr> <tr><td style="padding: 2px;">25</td><td style="padding: 2px;">Pumpoff Setpoint</td></tr> <tr><td style="padding: 2px;">26</td><td style="padding: 2px;">Low Fluid Load</td></tr> <tr><td style="padding: 2px;">27</td><td style="padding: 2px;">Pump Fillage Setpoint</td></tr> <tr><td style="padding: 2px;">28</td><td style="padding: 2px;">Peak Power</td></tr> <tr><td style="padding: 2px;">29 - 31</td><td style="padding: 2px;">Reserved</td></tr> </tbody> </table>							Bit	Function	0 - 15	Reserved	16	Peak Load	17	Min Load	18	Logic Expression	19	Peak Torque	20	Low Motor RPM	21	No RPM	22	No Crank	23	Belt Slippage	24	Malfunction Setpoint	25	Pumpoff Setpoint	26	Low Fluid Load	27	Pump Fillage Setpoint	28	Peak Power	29 - 31	Reserved
Bit	Function																																					
0 - 15	Reserved																																					
16	Peak Load																																					
17	Min Load																																					
18	Logic Expression																																					
19	Peak Torque																																					
20	Low Motor RPM																																					
21	No RPM																																					
22	No Crank																																					
23	Belt Slippage																																					
24	Malfunction Setpoint																																					
25	Pumpoff Setpoint																																					
26	Low Fluid Load																																					
27	Pump Fillage Setpoint																																					
28	Peak Power																																					
29 - 31	Reserved																																					
42222	1				Pump off SP select =bit9 Pump Fillage select =b1	Pump off selection fillage or set point																																
42223	1				Low RPM Limit																																	
42224	1				Consecutive Low RPM Allowed																																	
42225	1				Low RPM Start Delay																																	
42226	1				Peak Load Limit																																	
42227	1				Consecutive Peak Load Allowed	load checked every 2 milliseconds																																
42228	1				Minimum Load Limit																																	

42229	1			Consecutive Min Load Allowed	load checked every 2 milliseconds
42241	1			Load Pumpoff Setpoint	Scaled
42242	1			Position Pumpoff Setpoint	Scaled x100
42243	1			Consecutive Pumpoff Strokes Allowed	

Downhole Configuration 42264-42272 # Registers 10

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42264	2	X			Reference Pump Fillage	Pump Fillage Set Point
42268	2	X			Damping Factor (Calc & Overwritten by POC)	Damping Factor
42271	1				Tubing Head Pressure	Tubing Head Pressure
42272	2	X			Tubing Gradient	Tubing Gradient

Pumping Unit Dimensions 42274-42288 # Registers 16

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42274	1				Pumping Unit Type	Pumping Unit Type 0 - Conventional 1 - Mark II 2 - Reverse Mark 3 - Torque Master 4 - Air Balance 5 - Beam Balance 6 - HG Bent Beam
42275	1				Crank Rotation	Crank Rotation 0 - Clockwise 1 - Counter Clockwise
42276	1				Unit API Size (BEI database see Appendix A)	replace counter balance angle
42277	2	X			R Dimension	only writeable if 42276 = 0 (Custom Unit)
42279	2	X			K Dimension	only writeable if 42276 = 0 (Custom Unit)
42281	2	X			C Dimension	only writeable if 42276 = 0 (Custom Unit)
42283	2	X			P Dimension	only writeable if 42276 = 0 (Custom Unit)
42285	2	X			A Dimension	only writeable if 42276 = 0 (Custom Unit)
42287	2	X			I Dimension	only writeable if 42276 = 0 (Custom Unit)
42289	1				Crank Hole #	

Rod Taper Information 42289-42302 # Registers 24

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42290	6			X	Rod Types	Rod Types 0 - Steel 1 - Fiberglass
42296	6			X	Taper Intervals	6 Rod Taper Intervals
42302	12	X		X	Taper Diameter	6 Rod Taper Diameters

Linear Pump Configuration 42351-42357 # Registers 3

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42351	1				Linear Pump Distance Between Sprockets	
42353	1				Linear Pump Sprocket Diameter	
42355	1				Linear Pump Malfunction Digital Out Channel	not in use

PIP Calculations 42389 # Registers 1

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42389	1				Tubing Head Pressure Source Select	0-Constant, 1-Analog

Rod / Pump Counters 42496 - 42449 # Registers 4

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42496	2		X		Rodometer	Rodometer
42498	2		X		Pumpometer	Pumpometer

VFD Configuration 42501 - 42517 # Registers 4

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42501	1				VFD Dead Band	VFD +/- dead band of pump off setpoint
42504	1				VFD Min Scaling	Min Speed Scaled x10
42505	1				VFD Max Scaling	Max Speed Scaled x10
42507	1				VFD Speed Increase	VFD Speed Increase, Percent of Full Scale
42508	1				VFD Speed Decrease	VFD Speed Decrease, Percent of Full Scale
42509	1				VFD Analog output 1 mode	AO1 output mode 0 = 0-20mA, 1 = 4-20mA
42517	1				VFD Speed Constant	VFD Speed Override Value
42518	1				VFD Max Working Speed	VFD Max Working Speed x10
42519	1				VFD Min Working Speed	VFD Min Working Speed x10

Communication Control Registers 42530 - 42554 # Registers 15

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42530	1				RTU Address	Com 0 used for Wifi or Spare
42531	1				Baud Rate	see table
42532	1				Data Bits	5 = 5 data, 6=6 data, 7=7 data, 8=8 data
42533	1				Stop Bits	1 = 1 stop, 2 = 2 stop, 3 = 1.5 stop
42534	1				Parity	0 = none, 1 = Even, 2 = Odd
42540	1				RTU Address	Com 1 wired to TB1
42541	1				Baud Rate	see table
42542	1				Data Bits	5 = 5 data, 6=6 data, 7=7 data, 8=8 data
42543	1				Stop Bits	1 = 1 stop, 2 = 2 stop, 3 = 1.5 stop
42544	1				Parity	0 = none, 1 = Even, 2 = Odd
42550	1				RTU Address	Com 2 Spare
42551	1				Baud Rate	see table
42552	1				Data Bits	5 = 5 data, 6=6 data, 7=7 data, 8=8 data
42553	1				Stop Bits	1 = 1 stop, 2 = 2 stop, 3 = 1.5 stop
42554	1				Parity	0 = none, 1 = Even, 2 = Odd

Baud Rate Designation	0 - 300 1 - 1200 2 - 2400 3 - 4800 4 - 9600 5 - 19200 6 - 38400 7 - 57600 8 - 115200
-----------------------	--

VFD Speed vs Position 42560 - 42573 # Registers 14

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42560	1				Speed Change Position 1 %	x 10
42561	1				Speed Change Position 2 %	x 10
42562	1				Speed Change Position 3 %	x 10
42563	1				Speed Change Position 4 %	x 10
42564	1				Speed Change Position 5 %	x 10
42565	1				Speed Change Position 6 %	x 10
42566	1				Speed Change Position 7 %	x 10
42567	1				SPM 1 % for Position 1	x 10
42568	1				SPM 1 % for Position 2	x 10
42569	1				SPM 1 % for Position 3	x 10
42570	1				SPM 1 % for Position 4	x 10
42571	1				SPM 1 % for Position 5	x 10
42572	1				SPM 1 % for Position 6	x 10
42573	1				SPM 1 % for Position 7	x 10
42576	1				VFD Speed Mode 0= Spd vs Pos 1=Const spd	
42577	1				VFD Constant Speed %	x 10

Digital Input Fault Config **42680 - 42693** **# Registers 14**

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42680	2				DI4 Fault Configuration	

Register	#	F	L	A	Name	Description
42680	1				DI4 Fault Type	Type 0 - Disabled 1 - High Level 2 - Low Level 3 - High Level with Reset 4 - Low Level with Reset
42681	1				DI4 Fault Status	Status 0 = NO Fault 1 = Faulted

42682	2				DI5 Fault Configuration	
42684	2				DI6 Fault Configuration	
42686	2				DI7 Fault Configuration	
42688	2				DI8 Fault Configuration	
42690	2				DI9 Fault Configuration	
42692	2				DI10 Fault Configuration	

Analog Input Fault Config **42710 - 42745** **# Registers 36**

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42710	6				AI2 Fault Configuration	

Register	#	F	L	A	Name	Description
42710	2	X			AI2 Fault Level	AI2 scaled value trip level if Fault Type is set to 1-4
42712	2	X			AI2 Fault Reset	AI2 scaled value reset level if Fault Type is set to 3 or 4
42714	1				Fault Type	Type 0 - Disabled 1 - High Level 2 - Low Level 3 - High Level with Reset 4 - Low Level with Reset
42715	1				Fault Status	Status 0 = NO Fault 1 = Faulted

42716	6				AI3 Fault Configuration	
42722	6				AI4 Fault Configuration	
42728	6				AI5 Fault Configuration	
42734	6				AI6 Fault Configuration	
42740	6				AI7 Fault Configuration	

Customer Use Registers **42800 - 42899** **# Registers 100**

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42800	100				Customer Use Volitale Modbus Registers	

Appendix A --- API Unit Number Database

Pumping Unit Dimensions **42276** **# Registers** **1**

Note: Use Function Code 03 to Read this Data. Use Function Code 6/16 to Write this Data

Register	# Regs	F	L	A	NAME	DESCRIPTION
42276	1				Unit API Size (BEI database see Appendix A)	0 = Custom Unit
						1 = C-57D-76-42
						2 = C-57D-89-42
						3 = C-57D-95-48
						4 = C-57D-109-48
						5 = C-57D-76-54
						6 = C-80D-109-48
						7 = C-80D-133-48
						8 = C-80D-119-54
						9 = C-80D-133-54
						10 = C-80D-119-64
			#			11 = C-114D-133-54
						12 = C-114D-173-54
						13 = C-114D-143-64
						14 = C-114D-173-64
			2			15 = C-114D-143-74
						16 = C-114D-119-86
						17 = C-160D-143-64
						18 = C-160D-173-64
						19 = C-160D-143-74
						20 = C-160D-173-74
						21 = C-160D-200-74
						22 = C-160D-173-86
						23 = C-160D-173-100
						24 = C-228D-173-74
						25 = C-228D-200-74
						26 = C-228D-213-86
						27 = C-228D-246-86
						28 = C-228D-173-100
						29 = C-228D-213-100
						30 = C-228D-213-120
						31 = C-320D-246-74
						32 = C-320D-213-86
						33 = C-320D-246-86
						34 = C-320D-256-100
						35 = C-320D-305-100
						36 = C-320D-213-120
						37 = C-320D-256-120
						38 = C-320D-256-144
						39 = C-456D-256-100
						40 = C-456D-213-120
						41 = C-456D-256-120
						42 = C-456D-305-120
						43 = C-456D-365-120

44 =	C-456D-256-144
45 =	C-456D-305-144
46 =	C-456D-305-168
47 =	C-640D-305-120
48 =	C-640D-365-120
49 =	C-640D-256-144
50 =	C-640D-305-144
51 =	C-640D-365-144
52 =	C-640D-305-168
53 =	C-640D-365-168
54 =	C-912D-305-144
55 =	C-912D-365-144
56 =	C-912D-427-144
57 =	C-912D-305-168
58 =	C-912D-365-168
59 =	C-912D-427-168
60 =	C-912D-305-192
61 =	C-912D-365-192
62 =	C-912D-427-192
63 =	C-912D-305-240
64 =	C-912D-365-240
65 =	C-912D-427-240
66 =	C-912D-470-240
67 =	C-1280D-427-168
68 =	C-1280D-305-192
69 =	C-1280D-365-192
70 =	C-1280D-427-192
71 =	C-1280D-305-240
72 =	C-1280D-365-240
73 =	C-1280D-427-240
74 =	C-1280D-470-240
75 =	C-1824S-365-192
76 =	C-1824S-427-192
77 =	C-1824S-470-192
78 =	C-1824D-365-216
79 =	C-1824D-427-216
80 =	C-1824D-470-216
81 =	C-1824D-305-240
82 =	C-1824D-365-240
83 =	C-1824D-427-240
84 =	C-1824D-470-240
85 =	M-114D-143-64
86 =	M-114D-173-64
87 =	M-114D-143-74
88 =	M-114D-173-74
89 =	M-114D-143-86
90 =	M-160D-173-74
91 =	M-160D-200-74
92 =	M-160D-173-86
93 =	M-160D-213-86
94 =	M-228D-173-74
95 =	M-228D-200-74

96 =	M-228D-213-86
97 =	M-228D-246-86
98 =	M-228D-173-100
99 =	M-228D-256-100
100 =	M-228D-213-120
101 =	M-228D-256-120
102 =	M-320D-256-100
103 =	M-320D-305-100
104 =	M-320D-213-120
105 =	M-320D-256-120
106 =	M-320D-305-120
107 =	M-320D-256-144
108 =	M-456D-256-120
109 =	M-456D-305-120
110 =	M-456D-365-120
111 =	M-456D-256-144
112 =	M-456D-305-144
113 =	M-456D-365-144
114 =	M-456D-305-168
115 =	M-456D-305-192
116 =	M-640D-305-120
117 =	M-640D-256-144
118 =	M-640D-305-144
119 =	M-640D-365-144
120 =	M-640D-305-168
121 =	M-640D-365-168
122 =	M-640D-305-192
123 =	M-912D-305-144
124 =	M-912D-365-144
125 =	M-912D-305-168
126 =	M-912D-365-168
127 =	M-912DS-427-168
128 =	M-912D-305-192
129 =	M-912DS-427-192
130 =	M-912D-305-216
131 =	M-912DS-365-216
132 =	M-1280D-427-192
133 =	M-1280D-427-216
134 =	M-1824D-427-216
135 =	RM-228D-173-74
136 =	RM-228D-200-74
137 =	RM-228D-213-86
138 =	RM-228D-246-86
139 =	RM-228D-173-100
140 =	RM-228D-213-100
141 =	RM-228D-256-100
142 =	RM-228D-213-120
143 =	RM-320D-246-86
144 =	RM-320D-256-100
145 =	RM-320D-305-100
146 =	RM-320D-213-120
147 =	RM-320D-256-120

148 =	RM-320D-305-120
149 =	RM-320D-256-144
150 =	RM-456D-256-120
151 =	RM-456D-305-120
152 =	RM-456D-365-120
153 =	RM-456D-256-144
154 =	RM-456D-305-144
155 =	RM-456D-365-144
156 =	RM-456D-305-168
157 =	RM-640D-256-120
158 =	RM-640D-305-120
159 =	RM-640D-256-144
160 =	RM-640D-305-144
161 =	RM-640D-365-144
162 =	RM-640D-427-144
163 =	RM-640D-305-168
164 =	RM-640D-365-168
165 =	RM-640D-305-192
166 =	RM-912D-305-144
167 =	RM-912D-365-144
168 =	RM-912D-427-144
169 =	RM-912D-305-168
170 =	RM-912D-365-168
171 =	RM-912D-427-168
172 =	RM-912D-305-192
173 =	RM-912D-365-192
174 =	RM-912D-427-192
175 =	RM-1280D-365-168
176 =	RM-1280D-427-168
177 =	RM-1280D-365-192
178 =	RM-1280D-427-192
179 =	RM-1824D-365-168
180 =	RM-1824D-427-168
181 =	RM-1824D-365-192
182 =	RM-1824D-427-192
183 =	TM-228D-173-74
184 =	TM-228D-200-74
185 =	TM-228D-213-86
186 =	TM-228D-246-86
187 =	TM-228D-173-100
188 =	TM-228D-213-100
189 =	TM-228D-256-100
190 =	TM-228D-213-120
191 =	TM-320D-246-86
192 =	TM-320D-256-100
193 =	TM-320D-305-100
194 =	TM-320D-213-120
195 =	TM-320D-256-120
196 =	TM-320D-305-120
197 =	TM-320D-256-144
198 =	TM-456D-256-120
199 =	TM-456D-305-120

200 =	TM-456D-365-120
201 =	TM-456D-256-144
202 =	TM-456D-305-144
203 =	TM-456D-365-144
204 =	TM-456D-305-168
205 =	TM-640D-256-120
206 =	TM-640D-305-120
207 =	TM-640D-256-144
208 =	TM-640D-305-144
209 =	TM-640D-365-144
210 =	TM-640D-427-144
211 =	TM-640D-305-168
212 =	TM-640D-365-168
213 =	TM-640D-305-192
214 =	TM-912D-305-144
215 =	TM-912D-365-144
216 =	TM-912D-427-144
217 =	TM-912D-305-168
218 =	TM-912D-365-168
219 =	TM-912D-427-168
220 =	TM-912D-305-192
221 =	TM-912D-365-192
222 =	TM-912D-427-192
223 =	TM-1280D-365-168
224 =	TM-1280D-427-168
225 =	TM-1280D-365-192
226 =	TM-1280D-427-192
227 =	TM-1824D-365-168
228 =	TM-1824D-427-168
229 =	TM-1824D-365-192
230 =	TM-1824D-427-192
231 =	A-114D-173-64
232 =	A-160D-200-74
233 =	A-228D-246-86
234 =	A-228D-173-100
235 =	A-320D-305-100
236 =	A-320D-256-120
237 =	A-456D-256-120
238 =	A-456D-365-120
239 =	A-456D-305-144
240 =	A-640D-365-120
241 =	A-640D-305-144
242 =	A-640D-427-144
243 =	A-640D-305-168
244 =	A-912D-427-144
245 =	A-912D-305-168
246 =	A-912D-427-192
247 =	A-912D-427-216
248 =	A-912D-470-240
249 =	A-1280D-305-168
250 =	A-1280D-427-192
251 =	A-1280D-427-216

252 =	A-1280D-470-240
253 =	A-1824D-427-192
254 =	A-1824D-427-216
255 =	A-1824D-470-240
256 =	A-2560D-470-240
257 =	B-25-53-30
258 =	B-25-67-30
259 =	B-25-56-36
260 =	B-25-67-36
261 =	B-40-89-36
262 =	B-40-76-42
263 =	B-40-89-42
264 =	B-40-76-48
265 =	B-50-89-42
266 =	B-50-89-48
267 =	B-50-89-54
268 =	B-57-109-42
269 =	B-57-109-48
270 =	B-57-76-54
271 =	B-80-109-42
272 =	B-80-109-48
273 =	B-80-76-54
274 =	B-80-76-64
275 =	B-80-119-64
276 =	B-114-143-64
277 =	B-114-133-74
278 =	B-114-119-86
279 =	B-114-119-100
280 =	HG C-80119-64
281 =	HG C-114-143-74
282 =	HG C-160-173-86
283 =	HG CW-228-173-100
284 =	HG CW-228-213-100
285 =	HG CW-320-256-144
286 =	HG CW-456-256-144
287 =	HG CW-456-305-168
288 =	HG CW-640-305-168
289 =	HG CW-640-365-192
290 =	HG CW-912-365-192
291 =	HG CW-912-427-168
292 =	HG CW-1280-427-192
293 =	HG CW-1280-427-216